

## RFS 117 RF Switch LOS / SATCOM



### Details

The RFS-117 allows easy manual switching between attached LOS and SATCOM antennas when installed on a PRC-117 or equivalent radio RF output connector. The pull-to-turn embedded switching mechanism provides secure selection. Threads are made of stainless steel while the compact body of the device is lightweight aluminum finished in anodized black.

### RFS 117 Specifications

<b>Frequency</b>	DC-512 MHz
<b>VSWR</b>	1.1:1 Max
<b>Isolation</b>	30dB Min
<b>Actuation</b>	Sealed Lever
<b>Connectors</b>	
<b>SATCOM</b>	BNC Female
<b>LOS</b>	BNC Female 3/4-16 Male Thread
<b>Radio</b>	BNC Male 3/4-16 Female Thread
<b>Weight</b>	.4 lbs
<b>Finish</b>	Black Anodize
<b>Environmental</b>	MIL-STD-810

[www.ultralifecorporation.com](http://www.ultralifecorporation.com)

2000 Technology Parkway, Newark, New York | 315-332-7100 | Fax: 315-331-7800

©2010 Ultralife Corporation • [www.ultralifecorp.com](http://www.ultralifecorp.com) • all specifications subject to change without notice  
 The information contained herein is for reference only and does not constitute a warranty of performance.

23 NOV 10 UBI-05270 REV: -