

RFS 117 RF Switch LOS / SATCOM



Details

The RFS-117 allows easy manual switching between attached LOS and SATCOM antennas when installed on a PRC-117 or equivalent radio RF output connector. The pull-to-turn embedded switching mechanism provides secure selection. Threads are made of stainless steel while the compact body of the device is lightweight aluminum finished in anodized black.

RFS 117 Specifications

Frequency	DC-512 MHz
VSWR	1.1:1 Max
Isolation	30dB Min
Actuation	Sealed Lever
Connectors	
SATCOM	BNC Female
LOS	BNC Female 3/4-16 Male Thread
Radio	BNC Male 3/4-16 Female Thread
Weight	.4 lbs
Finish	Black Anodize
Environmental	MIL-STD-810

www.ultralifecorporation.com

2000 Technology Parkway, Newark, New York | 315-332-7100 | Fax: 315-331-7800

©2010 Ultralife Corporation • www.ultralifecorp.com • all specifications subject to change without notice
 The information contained herein is for reference only and does not constitute a warranty of performance.

23 NOV 10 UBI-05270 REV: -